

Bollard SQ2

B-6SQ-RT-DB-SM-SG

Dark Bronze Anodized Aluminum (710)

Phone: 877.421.9490
Fax: 877.421.3158
customerservice@wikk.com



Switch Sold Separately

Specification Summary

Bollard overview:

1. Manufacturer: **Wikk® Industries Inc.**
2. Model: **B-6SQ-RT-DB-SM-SG**
3. Height: 42" (1067 mm)
4. Shape: 6" square (152 mm x 152 mm)
5. Material: Aluminum Type 6063 T-5, .135" wall (3.4 mm)
6. Finish: Dark Bronze Anodized (710)
7. Top: Removable Black Marine Board Cap
8. Mount: Concealed Surface Mount
9. Single Gang Prep at 36" AFF (914 mm)
10. Country of Origin: Made in the U.S.A.

Optional add-ons:

- Transmitter & receiver pair for wireless applications (available in 433 or 868 MHz)

Optional finishes:

- Clear anodized aluminum (628)
(Use Part No. B-6SQ-RT-CL-SM-SG)

Countless custom options available!

Contact Wikk for custom short specs or budgetary and design assistance.

To ensure competitive bidding by qualified Sub Contractors, please specify Wikk's products in CSI Divisions: 8, 14, or 28.

Features & Benefits

Competitive 2-day lead time

Ships from the factory to the job site in two business days or less.

Simple installation

Easy install of base mounting bracket and bollard body with stainless hardware and standard tools. Body can be detached from base without disturbing flooring for maintenance or replacement.

Secure mounting

1/2" diameter masonry anchors provided for mounting on pavers, concrete, or other flooring materials.

Weather-resistant cap secured with stainless steel set screws

Easy removal of leak-free mortised black marine board cap to access internal wiring. Cap material is resistant to fading or cracking in all environments.

Switch actuator height at 36" AFF

Compatible with all Wikk 4R, 4X4, 6R, 6X6, and SG actuators, as well as any device requiring single gang mounting.

Robust structure

Solid and reliable aluminum construction for both indoor and outdoor locations.

Wireless operation (Optional)

Transmitter & battery secured directly under the removable cap for optimal transmission signal and convenient maintenance.

